

Temporary Power Distribution

SM5 (PSOA)

- PORTABLE SOCKET OUTLET ASSEMBLY, 5 X 10 AMP WITH 10 AMP PLUG



APPLICATIONS

A safe and portable socket outlet assembly (PSOA) for use on construction sites or at outdoor events.

CONSTRUCTION

- 5 x 10A sockets: 250V, 50Hz, IP66, RCB0 protected
- 10A industrial plug on 1.8m heavy duty lead (AS/NZS 3191)
- Supply 10A, 230/240V single phase + N + E
- RCBO 2 pole 10A 30mA 230/240V
- IP65 enclosure
- 3.5kg with cable and plug
- Meets requirements of AS/NZS 3012 & 3190
- Dimensions 325mm (L) x 295mm (H) x 270mm (W)

PRODUCT FEATURES

- Bright, visible and safe
- Weathertight: IP65 enclosure + IP66 outlets
- Robust and rugged enclosure with durable handle
- Overall RCBO protection
- · Tested and certified
- Ground clearance

Product Code	Cable Size (m)	Supply Power	Socket Outlets
SM5	1.8	10A, 230/240V – single phase + N + E	5 x 10A, 250V, 50Hz, IP66 RCB0 protected

SM6 (PSOA)

- PORTABLE SOCKET OUTLET ASSEMBLY, 6 X 15 AMP OUTLETS WITH 10 AMP PLUG

APPLICATIONS

Residential and light commercial building sites or at indoor/outdoor events.

CONSTRUCTION

- 6 x 15A sockets single phase 3P
- 10A industrial plug on 1.8m heavy duty lead (AS/NZS 3191)
- Frequency 50Hz
- Supply 10A, 230V/240V single phase + N + E
- RCBO 2 Pole 10A 30mA 230/240V
- IP44/IP65
- Specially blended polyethylene enclosure
- Meets AS/NZS 3190:2011 and AS/NZS 3012:2010
- Dimensions 412mm (L) x 280mm (H) x 268mm (W)

PRODUCT FEATURES

- 2 Year limited warranty
- Industrial lead and plug
- Stackable for storage and transportation
- 40mm ground clearance
- Third party tested and certified
- Impact resistant robust enclosure for outdoor use
- Assembled with standard industrial sockets allowing hassle free replacement
- Customisation available on request
- Assembled with trade tested components
- Designed for NZ & AU conditions

Product Code	Cable Size (m)	Supply Power	Socket Outlets	Weight (kg)
SM6	1.8	10A, 230/240V – single phase + N + E	6 x 15A single phase 3P	6

Powerplex has taken every precaution to ensure accurate information on this data page, but accept no liability for any errors or omissions. Powerplex reserves the right to modify specifications at any time.